

DATA SHEET

STU-F1001C-I

Serial RS-232, RS-422/485 to USB Converter with Optical Isolation

Port Configuration

- 1*RS-232/422/485 +
1*USB

Operating Temperature

- 0~70°C

Key Features

- ESD 15KV protection in RS-422/485 port
- USB 1.1 and USB 2.0 Forward Compatible
- Surge protection in RS-422/485 port.
- Support 3KV DC to DC optical isolation protection in serial port
- Built in 120ohm terminal resister with software selection ON/OFF.
- DIP switch ON/OFF to compensate signal attenuation in long distance connection at RS-485/422
- Auto detect the RS-422 or RS485 serial type



STU-F1001C-I – the combo serial port (RS-232/422/485) to USB converter with 0 ~70°C operating temperature, provide a flexible interface for industrial automation.

STU-F1001C-I serial to USB converter has one serial combo port and one USB port for harsh industrial environments. The combo port with RS-232/RS-422/RS-485 supports a flexible interface to connect to the equipment. Having wider operating temperature ranging from 0 to 70°C is better for lite-industrial application. The STU-F1001C-I with a compact size which supports wall mounting installation can set up the serial to Ethernet network more easily.

The converter including 3KV optical isolation, 15KV ESD protection and high surge protection can provide high reliable serial communication network.

Hardware Specifications

| | |
|--------------------|--------------------------------|
| Port Configuration | 1*RS-232/RS-422/485 + 1*USB |
|--------------------|--------------------------------|

RS-232

| | |
|-----------|------------------------------------------------|
| Connector | DB-9 |
| Signals | Rx , Tx , GND , RTS , CTS , DTR , DSR , DCD |

RS-422/485

| | |
|-------------------|----------------------------------------------|
| Connector | Terminal block (4-pin) |
| Signals | RS-422: TX+, TX-, RX+, RX- RS-485: D+, D- |
| Surge Protection | Supported |
| Built in Terminal | Supported |

Serial Communication

| | |
|----------------------------|--------------------------------------------------------------|
| Auto Detection | RS232/RS-422/485 Signal |
| Baud rate | RS-232 300bps~921.6kbps RS-422/485 300bps~230.4kbps |
| ESD protection | 15KV |
| Surge protection | RS-422/485 |
| Over Current Protection | RS-422/485 |
| Optical Isolation | 3KV |

USB

| | |
|-----------|-------------|
| Compliant | 1.0/1.1/2.0 |
| Connector | Type B |

Management

| | |
|----------------------------|-------------------------------------------------------------------------------|
| Driver Support | Windows -98SE/ 2000/ XP/ 2003/ VISTA/ WIN-7 Mac Osx/Os9 , Linux 2.4/2.6 |
| Over current protection | Supported |
| Power Input voltage | USB BUS Power 5V DC |
| Power consumption | 3Watt (Max) |
| Operating Temperature | 0°C~70°C |
| Operating Humidity | 5 to 95% RH (non-condensing) |
| Mounting | Wall-Mounting |
| Storage Temperature | -20°C~85°C |
| Storage Humidity | 5 to 95% RH (non-condensing) |
| Housing Protection | Plastic |
| Dimensions (WxHxD mm) | 88x27x91 |
| Weight | 94g |
| EMI | CE FCC Part15 class A |

Ordering Information

| Part Number | Description |
|--------------|------------------------------------------------------------------------------------------|
| STU-F1001C-I | 1*RS-232/RS-422/485 + 1*USB serial to USB converter with optical isolation (0°C~70°C) |